


Couplings

Chemtrol
Fig. No.

5101 Socket Couplings (S x S)



Nominal Size	Universal Part No.	Approx. Lbs./Ea.	Dim. N
1/4	1829-002	0.06	0.12
1/2	1829-005	0.10	0.24
3/4	1829-007	0.14	0.24
1	1829-010	0.22	0.24
1 1/4	1829-012	0.31	0.24
1 1/2	1829-015	0.40	0.24
2	1829-020	0.57	0.24
2 1/2	1829-025	0.73	0.19
3	1829-030	1.12	0.18
4	1829-040	1.94	0.18
6	1829-060	4.01	0.23
8*	1829-080	9.23	0.22
10	1829-100	14.62	0.35
12	1829-120	25.26	0.46

5101-R Reducing Socket Coupling (S x S)


Nominal Size	Universal Part No.	Approx. Lbs./Ea.	Dim. N
3/4 x 1/2	1829-101	0.13	0.43
1 x 1/2	1829-130	0.20	0.66
1 x 3/4	1829-131	0.20	0.54
1 1/4 x 3/4	1829-167	0.28	0.71
1 1/4 x 1	1829-168	0.30	0.59
1 1/2 x 1/2	1829-209	0.37	XXX
1 1/2 x 3/4	1829-210	0.35	0.75
1 1/2 x 1	1829-211	0.36	0.62
1 1/2 x 1 1/4	1829-212	0.38	0.50
2 x 1	1829-249	0.50	0.73
2 x 1 1/2	1829-251	0.54	0.48
3 x 2	1829-338	1.08	1.23
4 x 2	1829-420	1.73	1.57
4 x 3	1829-422	1.98	1.18

Other Reducing Couplings are produced by solvent cementing Reducer Bushings into Socket Couplings. They may be ordered as factory fabrications or may be assembled in the field.

Chemtrol

Fig. No.

5101-3-3 Thread Coupling (FPT x FPT)



Nominal Size	Universal Part No.	Approx. Lbs./Ea.	Dim. L
1/4	1830-002	0.07	1.40
1/2	1830-005	0.08	2.02
3/4	1830-007	0.13	2.27
1	1830-010	0.21	2.52
1 1/4	1830-012	0.31	2.77
1 1/2	1830-015	0.46	3.02
2	1830-020	0.64	3.27
2 1/2	1830-025	0.89	3.75
3	1830-030	1.30	3.99
4	1830-040	2.31	4.74

5101-3-3-R Reducing Thread Coupling (FPT x FPT)

Nominal Size	Universal Part No.	Approx. Lbs./Ea.	Dim. L
3/4 x 1/2	1830-101	0.15	2.33
1 x 1/2	1830-130	0.22	2.69
1 x 3/4	1830-131	0.23	2.69
1 1/4 x 3/4	1830-167	0.32	2.99
1 1/4 x 1	1830-168	0.34	2.99
1 1/2 x 3/4	1830-210	0.39	3.15
1 1/2 x 1	1830-211	0.40	3.15
1 1/2 x 1 1/4	1830-212	0.42	3.15
2 x 1	1830-249	0.53	3.39
2 x 1 1/2	1830-251	0.58	3.39

Other Reducing Couplings are produced by solvent cementing Reducer Bushings into Socket Couplings. They may be ordered as factory fabrications or may be assembled in the field.